

Energy Pro 2 - Parameters

- 2 channel amplifier

Input power: 11-15V

Power @ 4 Ohm: 200W x 2

Power @ 2 Ohm: 300W x 2

Bridge output @ 4 Ohm: 500W x 1

Frequency response: 10Hz-55KHz (-3db)

Channel separation: 60dB

S/N ratio: 100dB

Input impedance: 22K Ohm

Input sensitivity: 250mV-2V

THD: <0.05%

High pass frequency: 50-500Hz

Low pass frequency: 50-500Hz

Dimension: L345mm x W190mm x H50mm

Parameters in Chinese for reference:

输入电源: 11-15V

功率输出: 200W x 2 (4 Ω) 300W x 2 (2 Ω)

桥接输出: 500W x 1 (4 Ω)

频率响应: 10Hz-55KHz (-3db)

通道分离: 60dB

信噪比: 100dB

输入阻抗: 22K Ohm

输入灵敏度: 250mV-2V

总谐波失真: <0.05%

高通频率: 50-500Hz

低通频率: 50-500Hz

尺寸: L345mm x W190mm x H50mm

Energy Pro 4 - Parameters

- 4 channel amplifier

Input power: 11-15V

Power @ 4 Ohm: 120W x 4

Power @ 2 Ohm: 180W x 4

Bridge output @ 4 Ohm: 300W x 2

Frequency response: 10Hz-55KHz (-3db)

Channel separation: 60dB

S/N ratio: 100dB

Input impedance: 22K Ohm

Input sensitivity: 250mV-2V

THD: <0.05%

High pass frequency: 50-500Hz

Low pass frequency: 50-500Hz

Dimension: L345mm x W190mm x H50mm

Parameters in Chinese for reference:

输入电源: 11-15V

功率输出: 120W x 4 (4 Ω) 180W x 4 (2 Ω)

桥接输出: 300W x 2 (4 Ω)

频率响应: 10Hz-55KHz (-3db)

通道分离: 60dB

信噪比: 100dB

输入阻抗: 22K Ohm

输入灵敏度: 250mV-2V

总谐波失真: <0.05%

高通频率: 50-500Hz

低通频率: 50-500Hz

尺寸: L345mm x W190mm x H50mm